



Four toroidal transformers of different sizes are shown side-by-side. Each transformer has a red ribbon tied around its center. The transformers are made of a light-colored material, possibly aluminum, and have a central hole. The sizes decrease from left to right.

*Small cubage, low temperature raise.

- Power Transformer
- Audio Transformer
- Three Phase Transformer
- Auto Transformer
- Control Transformer
- Power Adapter
- Special Transformer

Model	Capacit y (VA)	Input (V)	Freque ncy (HZ)	Output (V)	Temperat ure raise ()	Formal Size		Weight kg	Fix-OS (mm)	screw (mm)
						H (mm)	D (mm)			
LB-30	30	220V	50	12	≤ 65	32	74	0.6	Φ6.5	M6
LB-50	50	220V	50	12	≤ 65	33	83	0.75	Φ6.5	M6
LB-80	80	220V	50	12	≤ 65	37	100	1.1	Φ6.5	M6
LB-105	105	220V	50	12	≤ 65	37	111	1.4	Φ8.5	M8
LB-120	120	220V	50	12	≤ 65	44	106	1.6	Φ8.5	M8
LB-150	150	220V	50	12	≤ 65	43	116	1.85	Φ8.5	M8
LB-190	190	220V	50	12	≤ 65	48	121	2.3	Φ8.5	M8
LB-240	240	220V	50	12	≤ 65	50	125	2.6	Φ8.5	M8
LB-300	300	220V	50	12	≤ 65	54	128	3	Φ8.5	M8
LB-500	500	220V	50	12	≤ 65	60	135	5.3	Φ8.5	M8

The Picture Of Formal Size

